

Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

HOME অনলাইনে অর্ডার করতে ভিজিট করুন v.munshiganjit.com.bd

A Super Store Of Computer & Electronics Accessoriess

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd





Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj



194, Banghabandhu Road Shomobay New Market (2nd Floor)

ASUS PRIME B450M-K II DDR4 AMD AM4 micro ATX Motherboard

Sale Price: 10500.0





PRODUCT ID: 00595

Basic

Information

Supported CPU AMD AM4 Socket for AMD Ryzen 5000 Series/ 5000 G-Series/ 4000 G-Series/ 3rd/2nd/1st Gen AMD Ryzen/ 2nd and

1st Gen AMD Ryzen with Radeon Vega Graphics/ Athlon with Radeon Vega Graphics Processors

AMD R450 Chipset

BIOS 256 Mb Flash ROM, UEFI AMI BIOS

Form Factor mATX Form Factor

8.9 inch x 8.7 inch (22.6 cm x 22.1 cm)

Expansion

Slots

PCI 3rd/2nd/1st Gen AMD Ryzen Processors

1 x PCle 3.0 x16 (x16 mode)

2nd and 1st Gen AMD Ryzen with Radeon Vega Graphics Processors

1 x PCle 3.0 x16 (x8 mode)

AMD Athlon with Radeon Vega Graphics Processors

1 x PCIe 3.0 x16 (x4 mode) AMD B450 chipset 2 x PCle 2.0 x1

M.2 Socket Total supports 1 x M.2 slot(s) and 4 x SATA 6Gb/s ports

3rd/2nd/1st Gen AMD Ryzen/ 2nd and 1st Gen AMD Ryzen with Radeon Vega Graphics:

1 x M.2 Socket 3, with M key, type 2242/2260/2280 storage devices support (SATA & PCI-E 3.0 x 4 mode)

Athlon with Radeon Vega Graphics Processors:

1 x M.2 Socket 3, with M key, type 2242/2260/2280 storage devices support (SATA mode)

AMD B450 chipset: 4 x SATA 6Gb/s port(s), Support Raid 0, 1, 10

Memory

Туре Dual Channel DDR4 Memory Technology



Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

A Super Store Of Computer & Electronics Accessoriess

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd







29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj



194, Banghabandhu Road, Shomobay New Market (2nd Floor)

Basic

Information

Slots	2 x DIMM
Supported Memory	4400(O.C.)/4000(O.C.)/3866(O.C.)/3733(O.C.)/3600(O.C.)/3466(O.C.)/ 3400(O.C.)/3300(O.C.)/3200(O.C.)/3000(O.C.)/2933(O.C.)/2800(O.C.) / 2666/2400/2133 MHz Un-buffered Memory
Maximum Memory	64GB

Graphics

Graphics Integrated Graphics in the 2nd and 1st Gen AMD Ryzen with Radeon Vega Graphics/ Athlon with Radeon Vega Graphics

> **Processors** 1 x D-Sub 1 x DVI-D 1 x HDMI 2.0b

Connector

& Ports

HDMI	1 x HDMI 2.0b
D-Sub (s)	1 x D-Sub
DVI-D (s)	1 x DVI-D
USB (s)	Rear USB Port (Total 6) 4 x USB 3.2 Gen 1 port(s)(4 x Type-A) 2 x USB 2.0 port(s)(2 x Type-A) Front USB Port (Total 6) 2 x USB 3.2 Gen 1 port(s) 4 x USB 2.0 port(s)
LAN Port (s)	Realtek RTL8111H ASUS LANGuard
Supported Storage	Total supports 1 x M.2 slot(s) and 4 x SATA 6Gb/s ports 3rd/2nd/1st Gen AMD Ryzen/ 2nd and 1st Gen AMD Ryzen with Radeon Vega Graphics: 1 x M.2 Socket 3, with M key, type 2242/2260/2280 storage devices support (SATA & PCI-E 3.0 x 4 mode) Athlon with Radeon Vega Graphics Processors: 1 x M.2 Socket 3, with M key, type 2242/2260/2280 storage devices support (SATA mode) AMD B450 chipset: 4 x SATA 6Gb/s port(s), Support Raid 0, 1, 10



Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

A Super Store Of Computer & Electronics Accessoriess 194, Banghabandhu Road, Shomobay New Market (2nd Floor)

Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd



Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



194, Banghabandhu Road Shomobay New Market (2nd Floor)

Basic

Information

Audio

Realtek ALC887/897 7.1-Channel High Definition Audio CODEC

- Supports: Jack-detection, Multi-streaming, Front Panel Jack-retasking, up to 24-Bit/192kHz playback

Audio Feature:

- LED-illuminated design

- Audio Shielding

- Dedicated audio PCB layers

- Premium Japanese audio capacitors

Choose the chassis with an HD audio module in the front panel to support 8-channel audio output.

Internal I/O **Ports**

1 x CPU Fan connector(s) (1 x 4 -pin)

1 x Chassis Fan connector(s) (1 x 4 -pin)

1 x USB 3.2 Gen 1(up to 5Gbps) connector(s) support(s) additional 2 USB 3.2 Gen 1 port(s) (19-pin)

2 x USB 2.0 connector(s) support(s) additional 4 USB 2.0 port(s)

1 x M.2 Socket 3 with M key, type 2242/2260/2280 storage devices support (SATA & PCIE 3.0 x 4 mode)

1 x SPI TPM header

1 x COM port(s) connector(s) 4 x SATA 6Gb/s connector(s) 1 x S/PDIF out header(s)

1 x 24-pin EATX Power connector(s) 1 x 8-pin ATX 12V Power connector(s) 1 x Front panel audio connector(s) (AAFP)

1 x System panel(s) 1 x Clear CMOS jumper(s)

1 x COM port header 1 x Speaker connector

TPM (Trusted Platform Module)

1 x SPI TPM header

Warranty

Information

Manufacturing Warranty

03 years

http://www.munshiganjit.com.bd