

Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

HOME जनलारेत जर्जात कतरण जिल्लिंग कतन www.munshiganjit.com.bd



Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj

A Super Store Of Computer & Electronics Accessoriess

194, Banghabandhu Road, Shomobay New Market (2nd Floor)

www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd

Shop No. 117-118,103-104, Chasara, Narayanganj-1400



194, Banghabandhu Road, Shomobay New Market (2nd Floor)



GIGABYTE B650M D3HP AX DDR5 AM5 Motherboard

Sale Price: 21000.0



PRODUCT ID: 02573

		•
$\mathbf{\nu}$	20	-
 \Box	ィゝ	"

Information

Information	
Supported CPU	AMD Socket AM5, support for: AMD Ryzen 8000/7000 Series Processors
Chipset	AMD B650
BIOS	1 x 256 Mbit flash Use of licensed AMI UEFI BIOS PnP 1.0a, DMI 2.7, WfM 2.0, SM BIOS 2.7, ACPI 5.0
Form Factor	Micro ATX Form Factor; 24.4cm x 24.4cm
Audio	Realtek Audio CODEC High Definition Audio 2/4/5.1/7.1-channel * You can change the functionality of an audio jack using the audio software. To configure 7.1-channel audio, access the audio software for audio settings.

Expansion Slots

PCI

1 x PCI Express x16 slot (PCIEX16), integrated in the CPU:

- AMD Ryzen 7000 Series Processors support PCIe 4.0 x16 mode

- AMD Ryzen 8000 Series-Phoenix 1 Processors support PCIe 4.0 x8 mode - AMD Ryzen 8000 Series-Phoenix 2 Processors support PCIe 4.0 x4 mode

* The PCIEX16 slot can only support a graphics card or an NVMe SSD. If only one graphics card is to be installed, be

sure to install it in the PCIEX16 slot.

Chipset:

- 1 x PCI Express x1 slot, supporting PCIe 3.0 and running at x1 (PCIEX1)

Memory

Туре	DDR5
Slots	4 DIMMs



Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

HOME অনলাইনে অর্ডার করতে ভিজিট করুন www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd v.munshiganjit.com.bd

Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj

194, Banghabandhu Road, Shomobay New Market (2nd Floor)

Shop No. 117-118,103-104, Chasara, Narayanganj-1400



194, Banghabandhu Road Shomobay New Market (2nd Floor)

Basic

Information

Supported Memory 7600(OC)/ 7200(OC)/ 7000(OC)/ 6800(OC)/ 6600(OC)/ 6400(OC)/ 6200(OC)/ 6000(OC)/ 5600(OC)/ 5200/ 4800

MT/s memory modules

Dual channel memory architecture

Support for non-ECC Un-buffered DIMM 1Rx8/2Rx8/1Rx16 memory modules

Support for AMD EXtended Profiles for Overclocking (AMD EXPO) and Extreme Memory Profile (XMP) memory

modules

Maximum Memory

192GB

Graphics

Graphics Integrated Graphics Processor with AMD Radeon™ Graphics support

- 2 x DisplayPorts, supporting a maximum resolution of 3840x2160@144 Hz

* Support for DisplayPort 1.4 version.

- 1x HDMI port, supporting a maximum resolution of 4096x2160@60 Hz

* Support for HDMI 2.1 version and HDCP 2.3.

 $\ensuremath{^{**}}$ Support for native HDMI 2.1 TMDS compatible ports.

Support for up to triple-display at the same time

(Graphics specifications may vary depending on CPU support.)

Connector &

Ports

HDMI	1x HDMI
Display Port (s)	2 x DisplayPorts
USB (s)	CPU: - 1 x USB Type-C port on the back panel, with USB 3.2 Gen 1 support - 1 x USB 3.2 Gen 1 port on the back panel - 1 x USB 2.0/1.1 port on the back panel Chipset: - 2 x USB 3.2 Gen 1 ports on the back panel - 1 x USB Type-C port with USB 3.2 Gen 1 support, available through the internal USB header - 2 x USB 3.2 Gen 1 ports available through the internal USB header - 5 x USB 2.0/1.1 ports (1 port on the back panel, 4 ports available through the internal USB headers)
LAN Port (s)	Realtek 2.5GbE LAN chip (2.5 Gbps/1 Gbps/100 Mbps)
Wireless Communication module	Realtek Wi-Fi 6E RTL8852CE - WIFI a, b, g, n, ac, ax, supporting 2.4/5/6 GHz carrier frequency bands - BLUETOOTH 5.3 - Support for 11ax 160MHz wireless (Actual data rate may vary depending on environment and equipment.)



Sales-01979490143, Corporate- 01979999722 CCTV-01979490147, Web team- 01979999711

HOME অনলাইনে অর্ডার করতে ভিজিট করুন www.munshiganjit.com.bd

A Super Store Of Computer & Electronics Accessoriess MITCare- 01979490145, Warranty-01979490146

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd

Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj 29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj





194, Banghabandhu Road, Shomobay New Market (2nd Floor)

Basic

Information

Supported Storage	 1 x M.2 connector (M2A_CPU), integrated in the CPU, supporting Socket 3, M key, type 2580 SSDs: - AMD Ryzen 7000 Series Processors support PCIe 4.0 x4/x2 SSDs - AMD Ryzen 8000 Series-Phoenix 1 Processors support PCIe 4.0 x4/x2 SSDs - AMD Ryzen 8000 Series-Phoenix 2 Processors support PCIe 4.0 x4/x2 SSDs 1 x M.2 connector (M2C_SB), integrated in the Chipset, supporting Socket 3, M key, type 22110/2280 PCIe 4. x4/x2 SSDs 4 x SATA 6Gb/s connectors
RAID	RAID 0, RAID 1, and RAID 10 support for NVMe SSD storage devices RAID 0, RAID 1, and RAID 10 support for SATA storage devices
Audio	3 x Audio jacks
Internal I/O Ports	Internal I/O Connectors 1 x 24-pin ATX main power connector 1 x 8-pin ATX 12V power connector 1 x CPU fan header 2 x system fan headers 2 x addressable LED strip headers 1 x RGB LED strip header 2 x M.2 Socket 3 connectors 4 x SATA 6Gb/s connectors 1 x front panel header 1 x front panel audio header 1 x USB Type-C header, with USB 3.2 Gen 1 support 1 x USB 3.2 Gen 1 header 2 x USB 2.0/1.1 headers 1 x Q-Flash Plus button 1 x reset jumper 1 x Clear CMOS jumper Back Panel Connectors 1 x USB 3.2 Gen 1 ports 2 x USB 3.2 Gen 1 ports 2 x USB 2.0/1.1 ports 1 x HDMI port 2 x DisplayPorts
	1 x RJ-45 port 3 x audio jacks
TPM (Trusted Platform Module)	1 x Trusted Platform Module header (For the GC-TPM2.0 SPI/GC-TPM2.0 SPI 2.0/GC-TPM2.0 SPI V2 module only)

Others



Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

HOME जनलारेत जर्जात कतरण जिल्लिंग कतन www.munshiganjit.com.bd

A Super Store Of Computer & Electronics Accessoriess

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd

OUR SHOP TECH BD21 Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj



194, Banghabandhu Road, Shomobay New Market (2nd Floor)

Basic

Information

Special Features Support for GIGABYTE Control Center (GCC)

* Available applications in GCC may vary by motherboard model. Supported functions of each application may also

vary depending on motherboard specifications.

Support for Q-Flash Support for Q-Flash Plus

Bundled Software Norton Internet Security (OEM version)

LAN bandwidth management software

Warranty

Information

Manufacturing Warranty

3 Years