

# Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 A Super Store Of Computer & Electronics Accessoriess MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

# HOME অনলাইনে অর্ডার করতে ভিজিট করুন www.munshiganjit.com.bd



Shop No-39, Level-4, Kassaf Shopping Center, Chittagong Road, Siddhirganj, Narayanganj



29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj

Sale Price: 9000.0

194, Banghabandhu Road, Shomobay New Market (2nd Floor)

www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd

Shop No. 117-118,103-104, Chasara, Narayanganj-1400



194, Banghabandhu Road, Shomobay New Market (2nd Floor)







PRODUCT ID: 02651

			•
 ĸ	1	C	
u	а	31	ľ

#### Information

information	
Supported CPU	Support for 8th Generation Intel® Core™ i7 processors/Intel® Core™ i5 processors/Intel® Core™ i3 processors/Intel® Pentium® processors/Intel® Celeron® processors in the LGA1151 package L3 cache varies with CPU
Chipset	Intel® H310 Express Chipset
BIOS	1 x 128 Mbit flash Use of licensed AMI UEFI BIOS PnP 1.0a, DMI 2.7, WfM 2.0, SM BIOS 2.7, ACPI 5.0
Form Factor	Micro ATX Form Factor; 22.6cm x 17.4cm

### **Expansion**

#### **Slots**

PCI 1 x PCI Express x16 slot, running at x16

(The PCIEX16 slot conforms to PCI Express 3.0 standard.)

2 x PCI Express x1 slots

(The PCI Express x1 slots conform to PCI Express 2.0 standard.)

#### Memory

Туре	DDR4
Slots	2 x DIMM sockets
Supported	Support for DDR4 2666/2400/2133 MHz memory modules
Memory	Support for ECC Un-buffered DIMM 1Rx8/2Rx8 memory modules (operate in non-ECC mode)
	Support for non-ECC Un-buffered DIMM 1Rx8/2Rx8/1Rx16 memory modules
	Support for Extreme Memory Profile (XMP) memory modules
	* To support 2666 MHz or XMP memory, you must install an 8th Generation Intel® Core™ i7/i5 processor.
Maximum	32 GB
Memory	



# Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 MITCare- 01979490145, Warranty-01979490146 CCTV-01979490147, Web team- 01979999711

### A Super Store Of Computer & Electronics Accessoriess

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd







29 DIT plot, Balur mat, 4th floor, Razzak villa, Chashara, Narayanganj



194, Banghabandhu Road, Shomobay New Market (2nd Floor)

#### Basic

#### Information

#### **Graphics**

Graphics

1 x D-Sub port, supporting a maximum resolution of 1920x1200@60 Hz 1 x HDMI port, supporting a maximum resolution of 4096x2160@30 Hz

\* Support for HDMI 1.4 version and HDCP 2.2.

Max Shared Memory

1GB

#### Connector &

#### **Ports**

USB (s)  4 x USB 3.1 Gen 1 ports (2 ports on the back panel, 2 ports available through the internal USB header) 6 x USB 2.0/1.1 ports (4 ports on the back panel, 2 ports available through the internal USB header)  LAN Port (s)  Realtek® GbE LAN chip (10/100/1000 Mbit)  4 x SATA 6Gb/s connectors  Audio  Realtek® ALC887 codec High Definition Audio 2/4/5.1/7.1-channel * To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channel feature through the audio driver.  Internal I/O Ports  1 x 24-pin ATX main power connector 1 x 4-pin ATX 12V power connector 4 x SATA 6Gb/s connectors 1 x CPU fan header 1 x system fan header 1 x front panel header 1 x front panel audio header 1 x USB 3.1 Gen 1 header 1 x USB 3.1 Gen 1 headers 1 x Clear CMOS jumper	HDMI	1 x HDMI port
Supported Storage  Audio  Realtek® ALC887 codec High Definition Audio 2/4/5.1/7.1-channel * To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channe feature through the audio driver.  Internal I/O Ports  1 × 24-pin ATX main power connector 1 × 4-pin ATX 12V power connector 4 × SATA 6Gb/s connectors 1 × CPU fan header 1 × system fan header 1 × front panel header 1 × front panel audio header 1 × USB 3.1 Gen 1 header 1 × USB 2.0/1.1 headers	USB (s)	
Storage  Audio  Realtek® ALC887 codec High Definition Audio 2/4/5.1/7.1-channel * To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channel feature through the audio driver.  Internal I/O Ports  1 x 24-pin ATX main power connector 1 x 4-pin ATX 12V power connector 4 x SATA 6Gb/s connectors 1 x CPU fan header 1 x system fan header 1 x front panel header 1 x front panel audio header 1 x USB 3.1 Gen 1 header 1 x USB 2.0/1.1 headers	LAN Port (s)	Realtek® GbE LAN chip (10/100/1000 Mbit)
High Definition Audio 2/4/5.1/7.1-channel *To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channel feature through the audio driver.  Internal I/O Ports  1 x 24-pin ATX main power connector 1 x 4-pin ATX 12V power connector 4 x SATA 6Gb/s connectors 1 x CPU fan header 1 x system fan header 1 x front panel header 1 x front panel audio header 1 x USB 3.1 Gen 1 header 1 x USB 2.0/1.1 headers	• •	4 x SATA 6Gb/s connectors
1 x 4-pin ATX 12V power connector  4 x SATA 6Gb/s connectors  1 x CPU fan header  1 x system fan header  1 x front panel header  1 x front panel audio header  1 x USB 3.1 Gen 1 header  1 x USB 2.0/1.1 headers	Audio	High Definition Audio 2/4/5.1/7.1-channel * To configure 7.1-channel audio, you have to use an HD front panel audio module and enable the multi-channel audi
	Internal I/O Ports	1 x 4-pin ATX 12V power connector  4 x SATA 6Gb/s connectors  1 x CPU fan header  1 x system fan header  1 x front panel header  1 x front panel audio header  1 x USB 3.1 Gen 1 header  1 x USB 2.0/1.1 headers
TPM (Trusted 1 x Trusted Platform Module (TPM) header (2x6 pin, for the GC-TPM2.0_S module only) Platform Module )	•	$1x$ Trusted Platform Module (TPM) header (2x6 pin, for the GC-TPM2.0_S module only)

# Warranty

#### Information

Manufacturing Warranty

03 Years



# Hotline-09614-502244

Sales-01979490143, Corporate- 01979999722 CCTV-01979490147, Web team- 01979999711

# HOME অনলাইনে অর্ডার করতে ভিজিট করুন www.munshiganjit.com.bd

A Super Store Of Computer & Electronics Accessoriess MITCare- 01979490145, Warranty-01979490146

194, Banghabandhu Road, Shomobay New Market (2nd Floor) Shop No. 117-118,103-104, Chasara, Narayanganj-1400 www.munshiganjit.com.bd e-mail-info@munshiganjit.com.bd









194, Banghabandhu Road, Shomobay New Market (2nd Floor)